

# TRION-1620-ACC/LV



- ▶ Sampling: 2 MS/s per channel at 16-bit; 24-bit in oversampling mode
- ▶ ADC: Low noise, SAR
- ▶ Input ranges
  - Voltage:  $\pm 5$  mV to  $\pm 100$  V
  - IEPE<sup>®</sup>:  $\pm 5$  mV to  $\pm 50$  V
- ▶ Isolated



## Module specifications

TRION-1620-ACC/LV specifications			
Input channels	TRION-1620-LV-6-BNC	6 channels BNC, voltage input	
	TRION-1620-ACC-6-BNC	6 channels BNC, voltage input; IEPE <sup>®</sup> ; 1 counter	
	TRION-1620-LV-6-L1B	6 channels 1B LEMO, voltage or current input, 1 to 28 V sensor supply, TEDS	
	TRION-1620-ACC-6-L1B	6 channels 1B LEMO, voltage or current input, IEPE <sup>®</sup> , 1 counter, sensor supply, TEDS	
Sampling rate / resolution	Highspeed mode	>1 to 2 MS/s	16-bit
	Over sampling mode	100 S/s to 1 MS/s	24-bit
Data transfer	16-bit / 24-bit		
Data rate DMA transfer	6 analog channels: max 24 MB/s; 1 x counter: max. 16 MB/s		
ADC type	SAR (Successive Approximation Register)		
Input ranges	– Voltage	$\pm 5$ mV, $\pm 10$ mV, $\pm 20$ mV, $\pm 50$ mV, $\pm 100$ mV, $\pm 200$ mV, $\pm 500$ mV, $\pm 1$ V, $\pm 2$ V, $\pm 5$ V, $\pm 10$ V, $\pm 20$ V, $\pm 50$ V, $\pm 100$ V,	
	– IEPE <sup>®</sup>	$\pm 5$ mV, $\pm 10$ mV, $\pm 20$ mV, $\pm 50$ mV, $\pm 100$ mV, $\pm 200$ mV, $\pm 500$ mV, $\pm 1$ V, $\pm 2$ V, $\pm 5$ V, $\pm 10$ V, $\pm 20$ V, $\pm 50$ V	
	– Current <sup>1)</sup>	$\pm 10$ mA, $\pm 20$ mA, $\pm 50$ mA, $\pm 100$ mA	
Accuracy <sup>3)</sup>	Voltage	DC to 1 kHz	$\pm 0.02$ % of reading $\pm 0.02$ % of range $\pm 20$ $\mu$ V
		>1 kHz to 5 kHz	$\pm 0.2$ % of reading $\pm 0.02$ % of range $\pm 20$ $\mu$ V
		>5 kHz to 10 kHz	$\pm 0.5$ % of reading $\pm 0.02$ % of range $\pm 20$ $\mu$ V
		>10 kHz to 50 kHz	$\pm 1.00$ % of reading $\pm 0.02$ % of range $\pm 20$ $\mu$ V
		>50 kHz to 100 kHz	$\pm 3.00$ % of reading $\pm 0.02$ % of range $\pm 20$ $\mu$ V
	Current <sup>1)</sup>	DC to 1 kHz	$\pm 0.1$ % of reading $\pm 0.02$ % of range $\pm 10$ $\mu$ A
		>1 kHz to 5 kHz	$\pm 0.2$ % of reading $\pm 0.02$ % of range $\pm 10$ $\mu$ A
		>5 kHz to 10 kHz	$\pm 0.5$ % of reading $\pm 0.02$ % of range $\pm 10$ $\mu$ A
>10 kHz to 50 kHz		$\pm 1.00$ % of reading $\pm 0.02$ % of range $\pm 10$ $\mu$ A	
>50 kHz to 100 kHz	$\pm 2.00$ % of reading $\pm 0.02$ % of range $\pm 20$ $\mu$ A		
MTBF <sup>4)</sup>	TRION-1620-LV-6-BNC: 230,318 h		
Input noise (5 mV range)	– 0 to 10 Hz	1.5 $\mu$ V <sub>pp</sub>	
	– Noise density	6.4 nV/SQRT(Hz)	

TRION-1620-ACC/LV specifications									
Input impedance	1 M $\Omega$ shunted by 18 pF								
Current input	Internal 10 $\Omega$ shunt; max. 100 mA protected with resettable fuse								
Input bias current	<1 nA								
Input coupling	DC; AC: 0.16Hz <sup>2)</sup>								
Gain drift	Typically 10 ppm/ $^{\circ}$ C max. 20 ppm/ $^{\circ}$ C								
Offset drift	Typically 0.3 $\mu$ V/ $^{\circ}$ C + 10 ppm of range/ $^{\circ}$ C, max 15 $\mu$ V/ $^{\circ}$ C + 20 ppm of range/ $^{\circ}$ C								
Linearity	Typically 0.01 %								
Input configuration	Isolated								
Isolation impedance	Isolation resistance >1 G $\Omega$ ; Isolation capacitance typically 15 pF								
Rated input voltage to earth according to EN 61010-2-30	33 V <sub>RMS</sub> , 46.7 V <sub>PEAK</sub> , 70 V <sub>DC</sub>								
Isolation voltage (channel-to-channel and channel-to-chassis)	1500 V <sub>PEAK</sub>								
Overvoltage protection	$\pm$ 300 V <sub>DC</sub>								
IEPE <sup>®</sup> excitation <sup>2)</sup>	4 mA, 8 mA $\pm$ 10 % @ 1 % $\pm$ 1 mV accuracy @ 24 V compliance voltage								
Voltage excitation <sup>1)</sup>	1 to 28 V @ 1 % $\pm$ 1 mV accuracy freely programmable (max. 100 mA, max. 1 W) per channel								
Typical signal-to-noise ratio, spurious	20 mV range			2 V range			100 V range		
Free SNR, effective number of Bits <sup>5)</sup>	SNR	SFDR <sup>6)</sup>	ENOB <sup>7)</sup>	SNR	SFDR <sup>6)</sup>	ENOB <sup>7)</sup>	SNR	SFDR <sup>6)</sup>	ENOB <sup>7)</sup>
Sample rate	[dB]	[dB]	[Bit]	[dB]	[dB]	[Bit]	[dB]	[dB]	[Bit]
0.1 kS/s	104	125	17.0	130	155	21.3	130	155	21.3
1 kS/s	97	125	15.8	123	150	20.1	122	145	20.0
10 kS/s	91	122	14.8	111	150	18.1	112	135	18.3
100 kS/s	82	116	13.3	106	142	17.3	105	130	17.1
200 kS/s	78.7	116	12.8	103.7	142	16.9	102	125	16.7
500 kS/s	74	114	12.0	99.5	140	16.2	98	121	16.0
1000 kS/s	71	87	11.5	93.2	130	15.2	93	116	15.2
2000 kS/s	56	56	9.0	88	88	14.3	88	88	14.3
Typical THD	-97 dB								
Typical CMR	<ul style="list-style-type: none"> <li>- <math>\leq</math>2 V range &gt;140 dB @ 50 Hz &gt;120 dB @ 1 kHz</li> <li>- &gt;2 V range &gt;90 dB @ 50 Hz &gt;60 dB @ 1 kHz</li> </ul>								
Low pass Filter (-3 dB, digital)	10 Hz, 30 Hz, 100 Hz, 300 Hz, 1 kHz, 3 kHz, 10 kHz, 30 kHz, 100 kHz, 300 kHz, 600 kHz								
– Characteristic	Bessel or Butterworth								
– Filter order	2 <sup>nd</sup> , 4 <sup>th</sup> , 6 <sup>th</sup> , 8 <sup>th</sup>								
Analog anti-aliasing filter	2 <sup>nd</sup> order Bessel, automatically selected								
Bandwidth (-3 dB, deactivated digital filter)	1 MHz 2 <sup>nd</sup> order Bessel filter								
Crosstalk fin 1 kHz [10 kHz]	$\leq$ 2 V Range: 120 dB [105 dB]								
Channel-to-channel phase mismatch	Typically <10 ns when using the same range; <60 ns for using different ranges								
Board-to-board phase mismatch	<30 ns								

Tab. 39: Module specifications

<b>TRION-1620-ACC/LV specifications</b>	
Counter	1x counter channel linked to analog channel #1; trigger level 70 % of actual analog input range
Counter modes	Event counting, period, frequency, pulse width, duty cycle
Counter input bandwidth	1 MHz to 10 kHz depending on analog filter of CH1
Counter time base	80 MHz
ESD protection	IEC61000-4-2: ±8 kV air discharge, ±4 kV contact discharge
Supported TEDS chips (LEMO only)	All common TEDS chips are supported.
Power consumption	Voltage mode: 6 W; IEPE® mode: 7.5 W

*Tab. 39: Module specifications*

- 1) TRION-1620-LV-6-L1B only
- 2) TRION-1620-ACC only
- 3) 1 year accuracy 23 °C ±5 °C
- 4) Mean time between failure
- 5) LP Filter in auto mode
- 6) SFDR excluding harmonics
- 7) ENOB calculated from SNR